

MMX-6-USB

6-Channel USB Microphone Mixer

- > Professional 6-channel stereo microphone mixer
- > USB 2.0 output
- > Balanced analog stereo line-level output
- > Individually selectable 48 Volt phantom power per input channel
- > Individually assignable output bus routing per input channel
- > Selectable 100 Hz low-cut output filter
- > Bi-color signal/clip LED indicator per input and master output
- > Screwdriver-adjustable controls
- > Compact, stackable "IFE medium" form factor
- > Surface or DIN rail mountable using bracket provided
- > Available rack mount option (sold separately)
- > External 100-240V universal power pack included



The MMX-6-USB is a compact and cost-efficient stereo microphone mixer, designed to allow up to six dynamic or condenser microphones to be connected to a [CaptureLiveHD®](#) system, or USB 2.0 audio system. Its unique housing design allows for installation virtually anywhere, including under a table, on a wall, or in an equipment rack. It can also be used as a microphone preamp for devices like the Capture HD® High-Definition Capture Recorder ([CAPTURE-HD](#)), which does not have a mic preamp on board.

Professional Features

To ensure compatibility with a full range of microphone types, the MMX-6-USB features individually selectable 48 Volt phantom power on each of its six inputs. Each input offers a 90 dB adjustment range, with up to 60 dB of gain available. Any input may be assigned to either or both channels of the mixer's stereo output. A low-cut filter is also provided at the output to reduce low-frequency rumble noise if required. Input and output indicators provide clear indication of signal presence and clipping for easy setup. All controls on the MMX-6-USB are screwdriver adjustable to prevent accidental changes to the settings once the unit is installed and set up.

USB and Analog Outputs

With both USB 2.0 and analog line-level outputs, the MMX-6-USB works with a wide range of devices and applications. Its USB output allows for direct connection to the Mac® or Windows® PC. The balanced analog output allows for connection to a stereo or mono line-level input on any conventional audio device. The USB and analog outputs contain the same audio signal and may be used simultaneously.

Integrator Friendly Enclosure

The MMX-6-USB features the Crestron IFE form factor, a compact "Integrator Friendly Enclosure" design that fits almost anywhere and enables a variety of installation options. Its shape allows multiple mixers and other IFE compliant devices to be stacked together. Using the included mounting bracket, it can be fastened to any flat surface or snapped onto a standard DIN rail. A rack mount kit is also available separately.

SPECIFICATIONS

Audio

A-D Conversion: 16-bit 48 kHz
Frequency Response: 20 Hz to 20 kHz, ±0.5 dB
S/N Ratio: 100 dB (single channel @ 0 dB level settings)
THD+N: < -100 dB
Crosstalk: >70 dB

Communications

USB: USB 2.0 device for connection to a codec, or a Mac® or Windows® PC

Connectors

12VDC 0.5A: (1) 2.5 x 5.5 mm DC power connector;
12 Volt DC power input;
PW-1205RU power pack included

G: (1) 4-40 screw, chassis ground lug

USB: (1) USB Type Mini-B 5-Pin, female;
USB 2.0 device port;
15 ft (5 m) mini-B 5-pin male to A male cable included

MMX-6-USB 6-Channel USB Microphone Mixer

AUDIO OUTPUT, L/R: (1) 5-pin 3.5 mm detachable terminal block;
Balanced/unbalanced stereo line-level audio output;
Output Impedance: 200 Ohms balanced, 100 Ohms unbalanced;
Maximum Output Level: 7.75 Vrms (+20 dBu) balanced, 3.88 Vrms (+14 dBu) unbalanced

INPUT 1 – 6: (6) 3-pin 3.5 mm detachable terminal blocks;
Comprises (6) balanced microphone audio inputs;
Input Level: 0.008 Vrms (-40 dBu) nominal, 0.775 Vrms (0 dBu) maximum;
Input Impedance: 2k Ohms balanced, 1k Ohms unbalanced;
Phantom Power: 48 Volts DC, selectable per channel

Controls & Indicators

BUS ASSIGN L/+R: (6) screwdriver-selectable 3-position slide switches, each switch routes the corresponding input to the left (L), right (R), or both (+) output buses

1 – 6 Level: (6) screwdriver-adjustable rotary controls, each adjusts the signal level for the corresponding input, level adjustment range is -80 to +10 dB

1 – 6 Signal: (6) bi-color green/red LEDs; each indicates signal presence (green) and clipping (red) for the corresponding input

LOW CUT: (1) screwdriver-selectable 2-position slide switch, enables or disables the 100 Hz low-cut output filter

MASTER Level: (1) screwdriver-adjustable rotary control, adjusts the output signal level, level adjustment range is -80 to +10 dB

MASTER Signal: (1) bi-color green/red LED, indicates post-fader signal presence (green) and clipping (red), onset of red indicates a signal level -2 dB from full scale, red at full brightness indicates full scale

PWR (rear): (1) green LED, indicates operating power supplied via the external power pack

PHANTOM POWER 1 – 6 (rear): (6) screwdriver-selectable 2-position slide switches with (6) red LEDs, each switch enables or disables phantom power and each LED indicates phantom power is enabled at the corresponding input

Power Requirements

Power Pack: 0.5 Amps @ 12 Volts DC;
100-240 Volts AC, 50/60 Hz power pack, model PW-1205RU included

Environmental

Temperature: 41° to 113° F (5° to 45 ° C)
Humidity: 10% to 90% RH (non-condensing)

Construction

Enclosure: IFE medium form factor, black and blue plastic
Mounting: Freestanding, stackable, surface mount, or 35 mm DIN EN 60715 rail mount; surface/DIN rail mounting bracket included, optional rack mount kit sold separately

Dimensions

Height: 1.37 in (35 mm);
1.78 in (46 mm) with bracket
Width: 7.01 in (178 mm);
7.35 in (187 mm) with bracket
Depth: 7.01 in (178 mm)

Weight

1.2 lb (545 g)

MODELS & ACCESSORIES

Available Models

MMX-6-USB: 6-Channel USB Microphone Mixer

Included Accessories

PW-1205RU: Wall Mount Power Pack, 12VDC, 0.5A, 2.5mm, Universal (Qty. 1 included)

Available Accessories

RMK-IFE-1U: IFE Rack Mount Kit

Notes:

This product may be purchased from an authorized Crestron dealer. To find a dealer, please contact the Crestron sales representative for your area. A list of sales representatives is available online at www.crestron.com/salesreps or by calling 800-237-2041.

The specific patents that cover Crestron products are listed online at: patents.crestron.com.

Certain Crestron products contain open source software. For specific information, please visit www.crestron.com/opensource.

Crestron, the Crestron logo, Capture HD, and CaptureLiveHD are either trademarks or registered trademarks of Crestron Electronics, Inc. in the United States and/or other countries. Mac is either a trademark or registered trademark of Apple Inc. in the United States and/or other countries. Windows is either a trademark or registered trademark of Microsoft Corporation in the United States and/or other countries. Shure is either a trademark or registered trademark of Shure Incorporated in the United States and/or other countries. Other trademarks, registered trademarks, and trade names may be used in this document to refer to either the entities claiming the marks and names or their products. Crestron disclaims any proprietary interest in the marks and names of others. Crestron is not responsible for errors in typography or photography. Specifications are subject to change without notice. ©2015 Crestron Electronics, Inc.