

CRESNET-NP-WH-SP1000

Cresnet® Control Cable, Non-Plenum, White, 1000 ft (304 m) spool



The Cresnet® bus is the communications backbone for many Crestron® keypads, lighting controllers, shade motors, sensors, and other devices. Cresnet is a simple, yet flexible 4-wire network that provides bidirectional communication and 24VDC power for Cresnet devices. Cresnet allows for both home run and daisy-chain wiring topologies, with cable lengths up to approximately 3000 feet (915 meters) per run.

Within a single non-plenum PVC jacket, CRESNET-NP contains (1) 18 AWG pair for 24VDC and Ground, and (1) 22 AWG shielded twisted pair for control data.

Specifications

Data Pair

Colors	Blue/white
Conductors	(2) 22 AWG (0.33 mm ²) stranded bare copper, twisted
Insulation	Polyethylene; Thickness: 0.015 in. (0.381 mm), nominal; Outer Diameter: 0.059 in. (1.499 mm), nominal
Shield	Aluminum/Polyester (100% coverage)
Drain	(1) 24 AWG (0.20 mm ²) stranded tinned copper

Power

Colors	Red/black
Conductors	(2) 18 AWG (0.82 mm ²) stranded bare copper
Insulation	PVC; Thickness: 0.010 in. (0.254 mm), nominal; Outer Diameter: 0.066 in. (1.676 mm), nominal
Shield	None

Outer Jacket

Material	PVC
Thickness	0.032 inch (0.813 mm) nominal
Outer Diameter	0.25 in. (6.35 mm) nominal

Environmental

Temperature -4° to 167°F (-20° to 75°C)

Weight

32 lb (14.5 kg)/1000 ft (304.8 m)

Compliance

NEC Article 800; UL Subject 13, Type CM; CSA Type CMG; RoHS

Model

CRESNET-NP-WH-SP1000

Cresnet® Control Cable, Non-Plenum, White, 1000 ft (304 m) spool

This product may be purchased from select authorized Crestron dealers and distributors. To find a dealer or distributor, please contact the Crestron sales representative for your area. A list of sales representatives is available online at www.crestron.com/How-To-Buy/Find-a-Representative or contact us for additional information by visiting www.crestron.com/contact/our-locations for your local contact.

The original language version of this document is U.S. English. All other languages are a translation of the original document.

The product warranty can be found at www.crestron.com/warranty.

The specific patents that cover Crestron products are listed online at www.crestron.com/legal/patents.

Certain Crestron products contain open source software. For specific information, please visit www.crestron.com/opensource.

Crestron, the Crestron logo, and Cresnet are either trademarks or registered trademarks of Crestron Electronics, Inc. in the United States and/or other countries. Other trademarks, registered trademarks, and trade names may be used in this document to refer to either the entities claiming the marks and names or their products. Crestron disclaims any proprietary interest in the marks and names of others. Crestron is not responsible for errors in typography or photography.

Specifications are subject to change without notice.

©2026 Crestron Electronics, Inc.

Rev 05/06/26