

CM2-AUX

Cameo® 2 In-Wall Multiway Remote



Shown in White Smooth, Custom Engraved

- Provides control to the connected dimmer or switch using a traveler wire in a traditional three- or four-way circuit ([CM2-DIMEX](#), [CM2-DIMUEX](#), and [CM2-SWEX](#), all sold separately)
- Line based multiway control for reliability across all load types
- 1- to 4-gang U.S. wall box installation using [Cameo® 2 multi-gang faceplates \(CM2-FP-G series, sold separately\)](#) or any decorator-style faceplate
- Available in eight different color and finish options
- Preinstalled large rocker button with default engraving or can be configured with a large rocker button with custom engraving
- Field replaceable rockers available to accommodate changes in device function, color, or engravings
- Blank large rockers available for engraving by a third-party

The [CM2-AUX](#) Cameo® 2 in-wall multiway remote controls Cameo 2 dimmers and switches. Its design matches the entire line of Cameo 2 dimmers, switches, and keypads, making it a great addition to new or retrofit installations.

NOTE: The CM2-AUX only accepts a rocker button and does not have an LED backlight. For multiway control using a device that accepts any style button and has LED backlighting, use a [CM2-KPEX](#).

- CM2-AUX-RKR-W-S ships in White Smooth with a preinstalled large rocker button.
- CM2-AUX-RKR ENGRAVED can be configured with a large rocker button with custom engraving and is available in the following finishes (specified in the custom engravings file):
 - W-S: White Smooth
 - W-T: White Textured
 - B-S: Black Smooth

- B-T: Black Textured
- A-S: Almond Smooth
- A-T: Almond Textured
- G-S: Gray Smooth
- G-T: Gray Textured

Engraving and finish options can be selected using the [Impress Engraving Software](#), [Crestron Home](#), or the [Crestron Home Online Configurator](#).

Multiway Dimming and Switching

Similar to traditional three- or four-way circuits, the CM2-AUX lets you control the lights from multiple locations using the traveler wire. Up to four devices can be connected to a single dimmer or switch. The [CM2-KPEX](#) provides button backlights and full keypad options while the CM2-AUX provides no button backlight and only accommodates a single large rocker button. The multiway controller provides instant usability upon installation without the need for programming.

NOTE: The CM2-AUX cannot be used to control a load directly. It must be used in conjunction with a [CM2-DIMEX](#), [CM2-DIMUEX](#), and [CM2-SWEX](#) (all sold separately).

Button Engraving

Functions of the rocker can be identified with custom, laser-etched engraving. Engraving is included with ENGRAVED models.

When a custom engraved model is ordered, the engraved buttons are installed on the device before it is shipped. Engraving files must be provided when ordering and can be created using Impress Custom Engraving Software, the Crestron Home® Setup app, or the Crestron Home Online Configurator. If necessary, custom engraving can be changed until the order is processed by emailing orders@crestron.com with the updated engraving file and order information.

To order replacement engravings, refer to the [CM2-BTNS ENGRAVED](#) buttons product page.

Multigang Expansion

Install Cameo® 2 devices side-by-side in a US multigang electrical box with a [CM2-FP-G](#) series faceplate or a third-party decorator faceplate.

Field Replaceable Buttons

Field-replaceable buttons allow for changes in device function or for the customer to use the system before finalizing the engravings. The buttons can be replaced with a custom engraved or blank CM2-BTNS rocker button.

Standard Wall Mount

Cameo 2 keypads fit standard US electrical wall boxes and all decorator form factor faceplates.

CM2-AUX

Cameo® 2 In-Wall Multiway Remote

Specifications

Power Requirements

Powered via connection to **REMOTE** terminal of a **CM2-DIMEX**, **CM2-DIMUEX**, **CM2-SWEX**, and line power input

Controls

Buttons Large rocker

NOTE: The CM2-AUX cannot be used to control a load directly. It must be used in conjunction with a CM2-DIMEX, CM2-DIMUEX, or CM2-SWEX.

Button Events Programmable for Normal, Tap, Double-Tap, and Press and Hold

Button Caps Includes one large rocker;
ENGRAVED models include custom engraved large rocker

Connections

HOT (1) 14-12 AWG, screw terminal, black, line power input
REM (1) 14-12 AWG, screw terminal, blue, remote
GND (1) 14-12 AWG, screw terminal, green, earth

Environmental

Temperature 32° to 86°F (0 °to 30°C)
Humidity 10% to 95% RH (noncondensing)

Construction

Mounting Mounts into any gang U.S. electrical box; 3.5 in. (26 mm) electrical box depth recommended

Dimensions

Height 4.06 in. (103 mm)
Width 1.75 in. (45 mm)
Depth 1.59 in. (40 mm)

Compliance

Regulatory Model: M202311005

FCC Part 15 Class B, IC Class B, CE, Intertek® Listed for US and Canada

Models

CM2-AUX RKR ENGRAVED

Cameo® 2 In-Wall Multiway Remote, Custom Engraved

CM2-AUX-RKR-W-S

Cameo® 2 In-Wall Multiway Remote, Standard Engraved, White Smooth

Available Accessories

For a list of available accessories, visit the [CM2-AUX](#) product page.

This product may be purchased from select authorized Crestron dealers and distributors. To find a dealer or distributor, please contact the Crestron sales representative for your area. A list of sales representatives is available online at www.crestron.com/How-To-Buy/Find-a-Representative or contact us for additional information by visiting www.crestron.com/contact/our-locations for your local contact.

The original language version of this document is U.S. English. All other languages are a translation of the original document.

The product warranty can be found at www.crestron.com/warranty.

The specific patents that cover Crestron products are listed online at www.crestron.com/legal/patents.

Certain Crestron products contain open source software. For specific information, please visit www.crestron.com/opensource.

Crestron, the Crestron logo, Cameo, Cresnet, Crestron Home, and infiNET EX are either trademarks or registered trademarks of Crestron Electronics, Inc. in the United States and/or other countries. Intertek is either a trademark or registered trademark of Intertek Group in the United States and/or other countries. The ETL logo is either a trademark or a registered trademark of Intertek Testing Services NA in the United States and/or other countries. UL is either a trademark or a registered trademark of Underwriters Laboratories, Inc. in the United States and/or other countries. Other trademarks, registered trademarks, and trade names may be used in this document to refer to either the entities claiming the marks and names or their products. Crestron disclaims any proprietary interest in the marks and names of others. Crestron is not responsible for errors in typography or photography.

Specifications are subject to change without notice.

©2026 Crestron Electronics, Inc.

Rev 01/07/26

CM2-AUX

Cameo® 2 In-Wall Multiway Remote

